

Feature Comparison	xSenso 2100	xSenso 21A2	xSenso 21R2
10/100 Ethernet	✓	✓	✓
USB Port (for configuration)	✓	✓	✓
Input Power (both may be used simultaneously for redundancy)	9-30 VDC Screw Block & Barrel Locking	9-30 VDC Screw Block & Barrel Locking	9-30 VDC Screw Block & Barrel Locking
DIN Rail Mount	✓	✓	✓
Browser Based Readings, Charting, Logging	✓	✓	✓
Email Alerts, SMTP w/ Authentication	✓	✓	✓
Modbus TCP	✓	✓	✓
SSL, SSH, 128-256bit AES Encryption	✓	✓	✓
HTTP/HTTPS POST Data to Cloud Server	✓	✓	✓
Industrial Operating Temperature	-40° to 85° C -40° to 185° F	-40° to 85° C -40° to 185° F	-40° to 85° C -40° to 185° F
Analog Inputs Voltage/Current Range: ±100mV, ±1V, ±10V, ±20mA	2	2	2
Analog Outputs Voltage/Current Range: 0-10V, 0-20mA	-	2	-
Relay Outputs	-	-	2